

IT6900A 系列宽范围可编程直流电源

- 功率范围涵盖100W到600W
- 高可见度的真空荧光显示屏 (VFD)
- 输出有开关控制
- 高准确度和高分辨率
- 低涟波和低噪音
- 采用智能型风扇控制，节约能源，降低噪音
- 可按照程序所编的电压电流值输出
- 可利用旋钮对电压和电流进行调节
- 可利用光标调节数字步进值
- 可设置定时输出时间 (0.1~99999.9秒)
- 标配有RS232/USB/GPIB通信接口



参数	IT6922A	IT6932A	IT6942A	IT6952A	IT6953A
额定值 (0 °C~40 °C)	电压	0 ~60V	0 ~60V	0~60V	0 ~150V
	电流	0~5A	0~10A	0~15A	0~25A
	功率	100W	200W	360W	600W
负载调节率 ±(% of output+offset)	电压	≤ 0.01%+3mV	≤ 0.01%+5mV	≤ 0.01%+8mV	≤ 0.01%+15mV
	电流	≤ 0.05%+2mA	≤ 0.05%+4mA	≤ 0.05%+6mA	≤ 0.1%+10mA
电源调节率 ±(% of output+offset)	电压	≤ 0.01%+3mV	≤ 0.01%+5mV	≤ 0.01%+8mV	≤ 0.01%+15mV
	电流	≤ 0.05%+2mA	≤ 0.05%+4mA	≤ 0.05%+6mA	≤ 0.1%+10mA
设定值解析度	电压	1mV	1mV	1mV	1mV(<100V) 10mV(>100V)
	电流	0.1mA	0.1mA	0.1mA	0.1mA
回读值解析度	电压	1mV	1mV	1mV	1mV(<100V) 10mV(>100V)
	电流	0.1mA	0.1mA	0.1mA(<10A) 1mA(>10A)	0.1mA(<10A) 1mA(>10A)
设定值精确度 (12个月内)(25°C±5°C) ±(% of output+offset)	电压	≤ 0.03%+5mV	≤ 0.03%+5mV	≤ 0.03%+5mV	≤ 0.03%+20mV
	电流	≤ 0.1%+5mA	≤ 0.1%+10mA	≤ 0.1%+15mA	≤ 0.1%+25mA
回读值精确度 (12个月内)(25°C±5°C) ±(% of output+offset)	电压	≤ 0.03%+5mV	≤ 0.03%+5mV	≤ 0.03%+5mV	≤ 0.03%+20mV
	电流	≤ 0.1%+5mA	≤ 0.1%+10mA	≤ 0.1%+15mA	≤ 0.1%+25mA
纹波 (20Hz ~20MHz)	电压	≤ 5mVp-p	≤ 8mVp-p	≤ 15mVp-p	≤ 20mVp-p
	电流	≤ 5mA rms	≤ 6mA rms	≤ 8mA rms	≤ 15mA rms
Sample rate 采样速率	10HZ				
尺寸 (mm)	214.5mmW×88.2mmH×354.6mmD			214.5mmW×88.2mmH×445mmD	
重量 (净重)	7.7Kg				